



**"Better Hearing,
Better Living."**

Contact Us

-  JSS Institute of Speech and Hearing
MG Road, Mysuru – 570004
-  jssish@jssonline.org
jssishmys@rediffmail.com
-  0821-2548229, 0821-2335014



JSS Mahavidyapeetha

JSS INSTITUTE OF SPEECH AND HEARING

Mahatma Gandhi Road, Mysuru 570004



**CARE AND MAINTENANCE OF
COCHLEAR IMPLANT**



CARE AND MAINTENANCE

Daily Care

- Wipe processor, coil, cable, and microphone port using dry-soft cloth.



- Detangle coil to avoid breakage.
- Check that the coil cable plug is not damaged and is properly plugged into the processor.

- Remove and clean batteries and contact points, brush connector points with a soft brush.



- Keep the processor in the Dry & Store unit when you're not using it, especially overnight.



- To clean the battery charger: Unplug it from the power adaptor and wipe the sockets with a soft, dry cloth.



- Avoid pulling/twisting cables or parts.
- Check for visible damage.
- Check skin around implant for irritation and redness.

Weekly Care

- Wipe battery charger sockets: If you see dirt in the battery holder, take out the batteries and clean the contacts with a cotton bud.

- Listening check using monitoring earphones: Use monitor earphones to check sound. Make sure the processor is on, lift the cover, and plug in the earphones. A parent or care taker can check if the mic picks up sound.



- Use coil wand to test coil functioning: Use the coil wand to check the coil. Hold it against the coil, and if the light turns on, the coil is working. If there's no light, contact your Audiologist.



- Clean contact points (battery module, magnet, etc.) with a soft brush.

Remember to Replace

- Microphone guard (every 3 months).
- Dry brick (every 2 months).
- O-ring (if battery cover loose).
- Safety line (if worn).
- Ear-hook (if worn or loose).
- Coil cable (if damaged).
- Coil (in case of physical damage).
- Battery (when completely drained).

